## **SCHAEFFLER**

We pioneer motion

# Changing APN setting on LTE-Stick



Although this document describes the way to change the APN on a Huawei E3372 LTE stick, the general steps described will also be the same for similar products from other brands.



**Important note!** An IMEI-lock on the SIM card may inhibit changing the settings. A new SIM card will very likely be unlocked. For details please check with your provider.

- Disconnect gateway from power source
- Open gateway housing and disconnect LTE stick
- Remove new SIM card for Gateway
- Insert the new SIM card into LTE stick.
  - It is recommended to use a large SIM card holder to ensure a proper connection of SIM card to modem



• Put LTE stick into PC.

• If Autorun is disabled on PC and you are entering a LTE stick into the PC for the first time, search for the removable drive in Windows Explorer and open it (takes a while before it appears)



#### Important note!

This operation may require admin rights on the computer you are using.

Dutei Start	nuels Freigeben Ansich									- 0	×
An Schnelzugriff Kag anheften	pieren Einfügen 🖌 Au Zwischenablage	sschneiden Id kopieren Innüpfung einfügen	pieren Lösch ach:*	بتر المعالم ال معالم المعالم ال	Neues Elemen Neuer Ordner Neu	att - Eigenschaft	en 🔁 Offinen = D Bearbeiten Werlauf Offinen	Altes auswählen Nichts auswählen Auswähl unikehren Auswählen			
6 +	> P05078089 > (Z)	) IU-H2R-I (\\schaeffler.com\\heraogen	vath(DATA) >	IPC > HWC > I	Products > OPTIME >	Documentation >	Manuals		v ð	"Manuals" durchsuchen	p
	^	Name		Änderungsdatum	Typ	Große					
🗸 🛊 Schnellzugriff		D 199510 Carrier Contract Contract	14 3030 E	17 10 3010 00 36	Manual Local As	20.00					
Desktop		Cartinito Belaciata cult	M ever, 34	17.10.2019 00:20	BOE WE HAR VE	20 NB					
Seveniceds	1	Elburt chicament has self		23.03.2020 08-34	PDF-WChange Vie.	429 KB					
Dokumente		RETSOLUND. 28: 91494 1112	120167- add	23.10.2019 07:37	PDF-XChange Vie	8.507 KB					
Sider		PVE ER17505.edf		18.10.2019 14.44	PDF-XChange Vie	529 KB					
HAVE		EVE. ER17505_SD.pdf		18.10.2019 14:44	PDF-XChange Vie	29 KB					
-		p00x_draft_front_sheet_outline	epdf	23.03.2020 08:17	PDF-XChange Vie	46 KB					
P05078089		Theon-Gateway Introduction	1.0.pdf	17.10.2019 08:26	PDF-XChange Vie	98 KB					
> 🧊 30-Objekte		Theon-Gateway-1111_DoC.pdf		17.10.2019 08-26	PDF-XChange Vie	131 KB					
> 📰 Bilder		Theon-Gateway-Quickstart-Gui	de-Safety	17.10.2019 08:25	PDF-XChange Vie	366 KB					
> Desktop											
> 🗟 Dokumente											
> L Downloads											
> h Musik											
and statement											
· · · · · · · · · · · · · · · · · · ·											
> a windows (c.)	°										
> U CD-Laufwen	K (Q) HLINK										
> 🛫 (K) APPS (\)	(#9003955)										
> = (U) NEGERW	VTA (\\ws00305550) T (\\schaeffler.com)										
CD-Laufwerk	(D) HiLink										
10 Elemente 1 Ele	ement ausgewählt (21,)	( Kill) Status 😗 Online									

#### • Execute "autorun.exe"

Conte Start Freinsban Ansid	Verwalten	CD-Laufwerk (D.) HiLink						- 0	×
An Schneitzugertt Expireren Einfügen	usschneiden fad kopieren erknüpfung einfügen	Verschieben Kapieren nach * Crganisieren	Demension Neuer Ordner Neuer	benent - ber Zugnitt - Eigenschaft	Ten 🖉 Ottnen -	Alles auswählen Nichts auswählen Auswahl umkehren Auswählen			
← → - ↑ 😝 > P05078089 > C	D-Laufwerk (D:) HiLink	x					v ð	"CO-Laufwerk (D.) HiLink"	du p
<ul> <li>Schwelbugett</li> <li>Desktop</li> <li>Desktop</li> <li>Desktop</li> <li>Dokumente</li> <li>Båder</li> <li>MAC</li> <li>SD-Objekte</li> <li>SBåder</li> <li>Desktop</li> </ul>	Name G HEinkapp Jip AcConfig.det Makheleficeru Makheleficeru Matholinere Urspisse Matholinere Urspisse Matholiner Ma	Andre 1405, 1511, 1511, 1511, 1511, 1511, 1501,	ungkalitium Typ 2020 11:56 ip Archive 2029 05:55 DAT-Datei 2029 05:55 DAT-Datei 2029 05:63 ip Archive 2029 05:63 ip Archive 2029 05:63 ip Archive 2029 05:63:51 Datei 2021 14:44 Setup-Inform 2021 05:50 SH-Datei 2021 00:50 SH-Datei	Grebe 392 K8 2 K8 32 K8 2 A20 K8 146 K8 233 K8 4 K8 4 K8 4 K8 4 K8 4 K8 4 K8 4 K8 4					
Columente     Deveniesds     Deveniesds     Windows (C)     Windows (C)     @ (C)_Laufwerk (D) HiLink     @ (C)_Laufwerk (D) HiLink     @ (C)_Laufwerk (D) HiLink     @ (C)_Laufwerk (D) HiLink     @ Laufwerk (D) HiLink		4							

- Webpage with IP address 192.168.8.1 opens automatically after a few moments. While the webpage design may change over time, the general structure of the steps taken to modify settings will remain very similar.
- Click Start



• Confirm Privacy Notice by clicking Next



#### • Click "Update Manually"

1NCE Portal   Verwalten Sie Ihre 🗆 🗙 📔 Neuer Tab	🗙 🛛 🚜 Hillink	🗙 🕐 Hünk	× +	- 0 ×
← → C ▲ Nicht sicher   192.168.8.1/html/guide.htm	d.			≅ ☆ 😝 :
	0	emight updates		
	0.	en grit op soles		
When Overnight update idle. Updating will use s	es is enabled, the device will automa ome data. Enable?	tically update to the latest version betw	veen 3:00-5:00 AM when the device is	
Choosing to disable thir 1. Missing the newly ad	s feature may result in the following: ided features.			
2. Less optimal user ex Vivu can access the Ove	perience due to data not being upda	ted property.		
	enight opcases searly again in Adr	need > operates.		
		and and controls		
	(	Update Manually		
	• • • • • • • • • • • • • • • • • • • •			

#### • Click on "Mobile Network"



• Activate "mobile data" and "data roaming" if not activated

🗏 HUAWEI		Lang	guage - I O 🛧 🔅
🕁 Homo	Mobile Network	BS Tools	Advanced
Internet Connection Mobile Network Searching	Internet Connection The Access Point Name (APN) is patienty Detwens your cartie's c has these settings in the system APN card connect to the internet Mobile dats Data roaming Auto-select network	the name for the settings your device n ebuar network and the public internet. Is files, and can fill in the APN information automatically, you can change the APN the setting of the setting of the setting of the setting of the setting of the setting of the setting of the setting of the setting of the forum of the changed.	eads to set up a connection to the Most of the time, your device already automatically when it connects. If the i manually.
		Profiles	+
	Ince(default) lot.fnce.net		
	em		

• Click **"+"** sign to add a new profile

	Mobile Network	BS Tools	Advanced
ternet Connection	Internet Connection The Access Point Name gateway between your o has these settings in the APN can't connect to the	n (APN) is the name for the settings your device re- ativity achildar network and the public interest. It system files, and can fill in the APN internation a internet automatically, you can change the APN	ads to set up a connection to the foot of the time, your device already automatically when it connects. If the manually.
	Mobile data Data roaming		
	Auto-select network	This feature will be disabled when the profil configuration is changed.	
		Profiles	+
	Ince(default) lot Ince.net		-
	em		

Profile name	Ince	
Set as Default Profile		
User name		
Password		
IP type	IPv4 & IPv6	Ŧ

### New provider

- Add new provider to profile name.
- Set as "Default Profile"; only the default profile will be used, even if several other profiles are listed.
- Leave username and password fields empty

• Scroll down and add the APN submitted for your provider, e.g. 1nce APN

Set as Default Profile		
User name		
Password		
IP type	IPv4 & IPv6	Ŧ
APN	iot.1nce.net	

- Click Save
- Put USB Stick into Gateway USB port via the short USB cable
- Check if after reboot (connecting gateway to power):
  - 1) Huawei stick permanently shines (blue or cyan)
  - 2) LED on gateway turns green (meaning the connection is established)



**Important note!** Sometimes it may be necessary to cycle the power again. Please do this if your LTE stick does not connect within five minutes.

#### Schaeffler Technologies AG & Co. KG

Industriestraße 1 – 3 91074 Herzogenaurach www.schaeffler.de industrial-services@schaeffler.com Tel. +49 2407 9149-66

In Deutschland: Telefon 0180 5003872 Aus anderen Ländern: Telefon +49 9132 82-0

Alle Angaben wurden sorgfältig erstellt und überprüft. Für eventuelle Fehler oder Unvollständigkeiten können wir jedoch keine Haftung übernehmen. Technische Änderungen behalten wir uns vor. © Schaeffler Technologies AG & Co. KG Ausgabe: 2021, September Nachdruck, auch auszugsweise, nur mit unserer Genehmigung.