


Rockwell N-Series to MDM N-Series Replacement Conversion Table

Description	Rockwell N-Series P/N	MDM N-Series P/N	MDM Dwg	Speed-Torque Curve	MDM N-Series Motor Configuration File			
					UltraMaster (Ultra 100/200)	Download	UltraWare (Ultra 3000)	Download
Motor, 1000 Line Encoder	N-2302-1-F00AA	T0601T0104	33030-004	T0601T0	T0601T0NSeriesMaster(N2302).mtr		T0601T0NSeriesWare(N2302).mxf	
Motor-24V Brake, 1000 Line Encoder	N-2302-1-F04AA	T0601T0105	Call Factory					
Motor, 1000 Line Encoder	N-2304-1-F00AA	T0601B8100	33030-004	T0601B8	T0601B8NSeriesMaster(N2304).mtr		T0601B8NSeriesWare(N2304).mxf	
Motor-24V Brake, 1000 Line Encoder	N-2304-1-F04AA	T0601B8101	Call Factory					
Motor, 2000 Line Encoder	N-3406-2-H00AA	T0851A0109	31030-078	T0851A0	T0851A0NSeriesMaster(N3406).mtr		T0851A0NSeriesWAre(N3406).mxf	
Motor-24V Brake, 2000 Line Encoder	N-3406-2-H04AA	T0851A0110	Call Factory					
Motor, 2000 Line Encoder	N-3412-2-H00AA	T0851C0103	31030-078	T0851C0	T0851C0NSeriesMaster(N3412).mtr		T0851C0NSeriesWAre(N3412).mxf	
Motor-24V Brake, 2000 Line Encoder	N-3412-2-H04AA	T0851C0106	Call Factory					
Motor, 2000 Line Encoder	N-4214-2-H00AA	T1101D0102	32030-047	T1101D0	T1101D0NSeriesMaster(N4214).mtr		T1101D0NSeriesWare(N4214).mxf	
Motor-24V Brake, 2000 Line Encoder	N-4214-2-H04AA	T1101D0103	Call Factory					
Motor, 2000 Line Encoder	N-4220-2-H00AA	T1101C6100	32030-047	T1101C6	T1101C6NSeriesMaster(N4220).mtr		T1101C6NSeriesWare(N4220).mxf	
Motor-24V Brake, 2000 Line Encoder	N-4220-2-H04AA	T1101C6101	Call Factory					
Motor, 2000 Line Encoder	N-5630-2-H00AA	T1101D3100	32030-050	T1101D3	T1101D3NSeriesMaster(N5630).mtr		T1101D3NSeriesWare(N5630).mxf	
Motor-24V Brake, 2000 Line Encoder	N-5630-2-H04AA	T1101D3101	Call Factory					
Motor, 2000 Line Encoder	N-5637-2-H00AA	T1102E0103	32030-052	T1102E0	T1102E0NSeriesMaster(N5637).mtr		T1102E0NSeriesWare(N5637).mxf	
Motor-24V Brake, 2000 Line Encoder	N-5637-2-H04AA	T1102E0103	Call Factory					
Motor, 2000 Line Encoder	N-5647-2-H00AA	T1102G3100	32030-052	T1102G3	T1102G3NSeriesMaster(N5647).mtr		T1102G3NSeriesWare(N5647).mxf	
Motor-24V Brake, 2000 Line Encoder	N-5647-2-H04AA	T1102G3101	Call Factory					

REVISIONS				
REV	ECN	DESCRIPTION	DATE	APP'D
A	DR8318	RELEASED	11/1/06	T.M.
B	ECN3230	ADDED CONFIG AND FRAME NOTES	07/03/07	J.S.

Clockwise rotation, viewed from the motor shaft, results in these waveforms.







ENCODER CONN WIRING CODE	
FROM	TO PIN
OUTPUT A	A
OUTPUT A'	B
OUTPUT B	C
OUTPUT B'	D
OUTPUT Z	E
OUTPUT Z'	F
CASE GROUND	G
N/A	H
+ 5 VDC	J
+ 5 VDC	K
COMMON	L
COMMON	M
N/A	N
N/A	P
THERMOSTAT	R
THERMOSTAT	S
OUTPUT W (H1)	T
OUTPUT U (H3)	U
OUTPUT V (H2)	V

MOTOR CONN. WIRING CODE	
FROM	TO PIN
MOTOR M1	A
MOTOR M2	B
MOTOR M3	C
CASE	D

NOTE:
TEMPERATURE SENSOR:
CONTACTS: NORMALLY CLOSED
MAX AMPS: 6 AMP
RATED VOLTAGE: 24VDC

USE MOTOR CONFIGURATION FILE FROM CMC PER MOTOR MODEL NUMBER



- NOTES:
1. ROTATION: CLOCKWISE MOTOR ROTATION VIEWING DRIVE END OCCURS WHEN PHASE A LEADS PHASE B, PHASE B LEADS PHASE C.
 2. THE INDEX PULSE OCCURS WHEN FACING THE MOTOR, THE SHAFT KEYWAY IS ORIENTED 90° ± 10° CLOCKWISE (MECHANICAL) FROM CONNECTORS.

FRAME: T1101 WITH NEMA 42 FLANGE

DIMENSIONS IN BRACKETS (DUAL) ARE IN MILLIMETERS

NOTICE Information contained herein is the sole property of Cleveland Motion Controls, Torque Systems Division. This may not be reproduced, copied or traced in any manner in part or whole without the written permission by Cleveland Motion Controls, Torque Systems Division.		MILLIMETERS (mm) TOLERANCES UNLESS OTHERWISE SPECIFIED: X ±0.25 XX ±0.125 XXX ±0.100 ANGLES ±0-30 THIRD ANGLE PROJECTION DIMENSIONS IN MILLIMETERS (mm) and inches (in) are given. Interpret dim. and tol. per ASME Y14.5M-1994.		APPLICATION NEXT ASSY USED ON 110mm DRAWN CHECKED APPROVED 1/25/07 MEZHER		CMC Cleveland Motion Controls An Ingersoll Rand Company Torque Systems Division TITLE OUTLINE N-4214, N-4220 ELECTROCRAFT REPLACEMENT SIZE D DWG. NO. 32030-047 REV B	
---	--	--	--	--	--	---	--

CAD FILE: 32030-047.SDDRW


CAD GENERATED DRAWING. DO NOT MANUALLY UPDATE.

SCALE: 1:1

SHEET 1 OF 1

REVISIONS				
REV	ECN	DESCRIPTION	DATE	APP'D
A	DR8318	RELEASED	11/1/06	T.M.
B	ECN3230	ADDED MTR CONFIG AND FRAME NOTES	07/03/07	J.S.

Clockwise rotation, viewed from the motor shaft, results in these waveforms.






ENCODER CONN WIRING CODE	
FROM	TO PIN
OUTPUT A	A
OUTPUT A'	B
OUTPUT B	C
OUTPUT B'	D
OUTPUT Z	E
OUTPUT Z'	F
CASE GROUND	G
N/A	H
+ 5 VDC	J
+ 5 VDC	K
COMMON	L
COMMON	M
N/A	N
N/A	P
THERMOSTAT	R
THERMOSTAT	S
OUTPUT W (H1)	T
OUTPUT U (H3)	U
OUTPUT V (H2)	V

MOTOR CONN. WIRING CODE	
FROM	TO PIN
MOTOR M1	A
MOTOR M2	B
MOTOR M3	C
CASE	D

NOTE:
TEMPERATURE SENSOR:
CONTACTS: NORMALLY CLOSED
MAX AMPS: 6 AMP
RATED VOLTAGE: 24VDC

B USE MOTOR CONFIGURATION FILE FROM CMC PER MOTOR MODEL NUMBER



NOTES:

1. ROTATION: CLOCKWISE MOTOR ROTATION VIEWING DRIVE END OCCURS WHEN PHASE A LEADS PHASE B, PHASE B LEADS PHASE C.
2. THE INDEX PULSE OCCURS WHEN FACING THE MOTOR, THE SHAFT KEYWAY IS ORIENTED 90° ± 10° CLOCKWISE (MECHANICAL) FROM CONNECTORS.

B FRAME: T1101 WITH NEMA 56 FLANGE

DIMENSIONS IN BRACKETS (DUAL) ARE IN MILLIMETERS	
NOTICE Information contained herein is the sole property of Cleveland Motion Controls, Torque Systems Division. This may not be reproduced, copied or traced in any manner in part or whole without the written permission by Cleveland Motion Controls, Torque Systems Division.	
MILLIMETERS (mm) TOLERANCES UNLESS OTHERWISE SPECIFIED: X ±.25 XX ±.025 XXX ±.010 ANGLES ±.1°-30° THIRD ANGLE PROJECTION DIMENSIONS IN MILLIMETERS (mm) AND INCHES (INCH) SHALL BE INTERPRETED AND TOL. PER ASME Y14.5M-1994.	
APPLICATION NEXT ASSY USED ON 110mm DRAWN T.MEZHER 1/29/07 CHECKED APPROVED	
FILE OUTLINE N-5630 ELECTROCRAFT REPLACEMENT SIZE D DWG. NO. 32030-050 REV. B SCALE 1:1 SHEET 1 OF 1	

CAD GENERATED DRAWING.
DO NOT MANUALLY UPDATE

CAD FILE: 32030-050.SDDRW

